

4

3

2

1

THIS DRAWING IS UNPUBLISHED.

RELEASED FOR PUBLICATION

© COPYRIGHT

ALL RIGHTS RESERVED.

LOC

DIST


REVISIONS

P	LTR	DESCRIPTION	DATE	DWN	APVD
	D2	ECR-14-003319	06MAR2014	GK	HMR

REPLACED BY OCEAN STYLE APPLICATOR PART
NUMBER 2266150-1

FOR REPLACEMENT PARTS FOR APPLICATOR 1426209
REFER TO ADDITIONAL PAGE(S). SPARE PARTS KIT (IF LISTED)
WILL REMAIN AVAILABLE.

THE REPLACEMENT OCEAN STYLE APPLICATOR HAS THE
SAME TERMINATOR/PRESS INTERFACE AS APPLICATOR
1426209

THIS DRAWING IS A CONTROLLED DOCUMENT.		DWN GOPALAKRISHNA HV		 TE Connectivity			
DIMENSIONS:		CHK RAGHAVENDRA					
		APVD RAGHAVENDRA		NAME SIDE FEED HD-I APPLICATOR			
		PRODUCT SPEC					
		APPLICATION SPEC					
MATERIAL		WEIGHT		SIZE A3	CAGE CODE	DRAWING NO C- 1426209	RESTRICTED TO
FINISH		CUSTOMER DRAWING		SCALE		SHEET 1 OF 2	REV D2

8

7

6

5

4

3

2

1

THIS DRAWING IS UNPUBLISHED.

RELEASED FOR PUBLICATION

BY TYCO ELECTRONICS CORPORATION. ALL RIGHTS RESERVED.

LOC

DIST

REV

DATE

BY

APPROVED

A

66

D1

ECR-07-016875

7-2007

MY

GB

PART NUMBER	REV	FIRST USED	TERMINATOR	FEED TYPE	DESCRIPTION
1426209-1	D	-	LEADMAKER	MECH POST FEED	CUTS CARRIER
1426209-2	D	-	BENCH	MECH PRE FEED	CUTS CARRIER
1426209-6	D	-	LEADMAKER	MECH POST FEED	CONTINUOUS CARRIER
7-1426209-1	D	-	LEADMAKER	MECH POST FEED	-1 AND SPARE PARTS
7-1426209-2	D	-	BENCH	MECH PRE FEED	-2 AND SPARE PARTS
7-1426209-6	D	-	LEADMAKER	MECH POST FEED	-6 AND SPARE PARTS
7-1426209-7	A	-	-	-	SPARE PARTS KIT

CRIMP DATA AMP TERMINAL AMP CRIMP SPECS

TERMINAL NAME: AMP MODU MOD IV REC, SHORT POINT OF CONTACT

CRIMP	SIZE	TYPE	RANGE
WIRE	1.40 [.055 IN]	F	24-20 AWG
INSUL	1.78 [.070 IN]	F	1.60 MAX [.065 IN MAX]

WIRE STRIP LENGTH 3.90-4.70 [.154-.185 IN]

APPL INSTRUCTION 408-8322

TERMINAL -

APPL SPEC 114-3118

FEED

TERMINALS APPLIED

WIRE SIZE mm² AWG	CRIMP HEIGHT	PIN PN AND LENGTH [IN]
20 AWG or 0.50mm²	0.89 ±0.05 [.035 ±.002 IN]	5-354779-6 [.3270]
22 AWG or 0.35mm²	0.79 ±0.05 [.031 ±.002 IN]	6-354779-4 [.3310]
24 AWG	0.69 ±0.05 [.027 ±.002 IN]	7-354779-3 [.3355]

SET UP GAGE 458637-3

LAYOUT L1426209

1. RECOMMENDED SPARE PARTS.

2. GREASE RAM, CAM, CAM FOLLOWER AND FEED ROD LIGHTLY.

3. LUBRICATE DAILY PER THE APPLICATOR INSTRUCTION SHEET SUPPLIED WITH THE APPLICATOR.

4. SEE CUSTOMER DRAWINGS FOR CUTT OFF REQUIREMENTS

VIEW B ROTATED 180°

POST FEED 40 mm STROKE

POST FEED 30 mm STROKE

PRE FEED 30 mm STROKE

PRE FEED 40 mm STROKE

THIS DRAWING IS A CONTROLLED DOCUMENT.

APPROVED

DATE

BY

NAME

PRODUCT SPEC

APPLICATION SPEC

WEIGHT

CUSTOMER DRAWING

SCALE

SHEET 1 OF 1

REV D1

QTY REQD PER ASSY

PARTS LIST

QTY	REQD	PER	ASSY	PART NO	DESCRIPTION	ITEM NO
-	1	1	1	1	1	73
-	1	1	1	1	1	72
-	1	1	1	1	1	71
-	1	1	1	1	1	70
-	1	1	1	1	1	69
-	1	1	1	1	1	68
-	1	1	1	1	1	67
-	2	2	2	2	2	66
-	1	1	1	1	1	65
-	1	1	1	1	1	64
-	1	1	1	1	1	63
-	1	1	1	1	1	62
-	2	2	2	2	2	61
-	1	1	1	1	1	60
-	1	1	1	1	1	59
-	1	1	1	1	1	58
-	1	1	1	1	1	57
-	1	1	1	1	1	56
-	1	-	-	-	-	55
-	4	4	4	4	4	54
-	2	2	2	2	2	53
-	1	1	1	1	1	52
-	1	1	1	1	1	51
-	1	1	1	1	1	50
-	-	-	-	-	-	49
-	1	1	1	1	1	48
-	1	1	1	1	1	47
-	1	1	1	1	1	46
-	1	1	1	1	1	45
-	1	1	1	1	1	44
-	1	1	1	1	1	43
-	1	1	1	1	1	42
-	1	1	1	1	1	41
-	1	1	1	1	1	40
-	1	1	1	1	1	39
-	1	1	1	1	1	38
-	1	1	1	1	1	37
-	1	1	1	1	1	36
-	1	1	1	1	1	35
-	2	2	2	2	2	34
-	1	1	1	1	1	33
-	1	1	1	1	1	32
-	1	1	1	1	1	31
-	1	1	1	1	1	30
-	1	1	1	1	1	29
-	1	1	1	1	1	28
-	2	2	2	2	2	27
-	1	1	1	1	1	26
-	1	1	1	1	1	25
-	1	1	1	1	1	24
-	1	1	1	1	1	23
-	1	-	-	-	-	22
-	1	1	1	1	1	21
-	4	4	4	4	4	20
-	-	-	-	-	-	19
-	1	1	1	1	1	18
-	1	-	-	-	-	17
-	2	2	2	2	2	16
-	1	1	1	1	1	15
-	-	-	-	-	-	14
-	1	1	1	1	1	13
-	2	2	2	2	2	12
-	2	2	2	2	2	11
-	-	-	-	-	-	10
-	1	1	1	1	1	9
1	2	2	2	1	1	8
-	1	1	1	1	1	7
-	1	1	1	1	1	6
-	1	1	1	1	1	5
-	1	1	1	1	1	4
1	2	2	2	1	1	3
-	1	1	1	1	1	2
1	2	2	2	1	1	1

AMP 4805 REV 31MAR2000

Translated 070103,105922, PYMMDD,HHMMSS from ComputerVision, Inc., Medusa Revision 12.2.51

CUSTOMER DRAWING

DRAWING NUMBER - 1426209 SHEET 2 OF 2 REV. D2

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9