



# ETA-USA

## High Quality Switching Power Supplies

*Flex.Power, Input 100/200Vac Auto-Select,*

2ch-3ch

110W

AC85-132 /  
AC170-264VAC

# WRDJ-FWX-X SERIES

## Output Table

REPAIR WARRANTY 1 YEAR



**INPUT AC100V/AC200V**

MODEL	OUTPUT			EFFICIENCY
	OUTPUT 1 (V1)	OUTPUT 2 (V2)		
WRDJ-21FWX	+5V:0.5~15A	+24V:3A Peak4A		75%
WRDJ-22FWX	+12V:0.2~7A	+12V:4.2A Peak5A		77%
WRDJ-23FWX	+15V:0.2~5.6A	+15V:3.6A		78%
WRDJ-24FWX	+5V:0.5~15A	+12V:6A Peak7A		75%
WRDJ-21FWX-B	+24V:0~4.3A Peak5A	(V3) +5V:1.5A		79%
	OUTPUT 1 (V1)	OUTPUT 2 (V2)	OUTPUT 3 (V3)	
WRDJ-01X	+5V:1~15A	+12V:4.2A Peak5A	-12V:1.2A	72%
WRDJ-03X	+5V:1~15A	+12V:4.2A Peak5A	-5V:1.5A	72%
WRDJ-04X	+5V:1~15A	+15V:3.6A	-15V:1A	72%
WRDJ-06X	+5V:1~15A	+24V:2.1A Peak3A	+12V:1.2A	72%

\* Output 1(V1) Required Minimum-Load for Output1(V1)=Main-Channel.


\* Please use within Maximum-Power 110W

## Applications

Communicators, Office Equip., Intelligence Equip.,  
Industrial Machines, Household Equip.

In the line of "WR" series which complied with world-wide input range, "WRDJ" series are 2 and 3 outputs types with 110 Watts, and also are input automatic select types, Such as remarkable Flexible-Power, Remote Control, Power-Fail and etc., Many functions such as are in it. Besides for the Safety and the Noise-EMI, it is complied with international standards, so we can call it "Global Power Supply."

## Output Derating



## Special Features

1. Flexible Power (using within Max.-Power 110W)
2. Attached Remote Control with ON-OFF Function
3. Comply with Peak-Current and Pulse-Load
4. Attached Power-Fail Signal
5. Safety: Based on UL1950, IEC950, VDE, CSA
6. Noise EMI: Based on FCCclassB, VDEclassB, VCCI-2 (JAPAN)
7. M T B F: 55,000hrs. (at 40 C)
8. OPUIONS
  - (1) Without Cover Type (add "O" to end of model name)
  - (2) Connector Output Type (add "S" to end of model name)
  - (3) (1)+(2) Type (add "SO" to end of model name)
  - (4) Input & Output Wire harness (Lead wire 40cm)



# Mouser Electronics

Authorized Distributor

Click to View Pricing, Inventory, Delivery & Lifecycle Information:

[ETA-USA:](#)

[WRDJ21FWX-U](#) [WRDJ24FWX-U](#) [WRDJ23FWX-U](#) [WRDJ22FWX-U](#)

## Данный компонент на территории Российской Федерации

### Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

### Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: [info@moschip.ru](mailto:info@moschip.ru)

Skype отдела продаж:

moschip.ru

moschip.ru\_4

moschip.ru\_6

moschip.ru\_9