

5744 Solder Saver[®]



Product Description

Kester 5744 Solder Saver[®] is a chloride-free, inorganic white powder formulated to remove dross, the oxide of solder, from still solder pots and wave soldering machines. Unlike most active reducing materials, 5744 does not decompose to sticky residues that are harder to remove than the original dross. 5744 has been designed to be low fuming and is stable at soldering temperatures and has been shown to be effective up to 380°C (720°F). This makes the 5744 a good candidate for both tin-lead and lead-free solder baths. Unlike flammable, messy, organic-based solder cover chemicals, 5744 is a non-flammable powder that remains a solid while it is working and is easily removed from the solder pot after it is used. Reducing tin oxide back to tin metal will greatly reduce dross scrap and will help keep the soldering pot surface clear of residues.



Physical Properties

Appearance: White Crystals

Melting Point: Sublimes >300°C

Flash Point: None



Application

5744 must be used on a still solder pot surface. All solder wave pumping and agitation action must be turned off. The pot temperature should be controlled to 232-260°C (450-500°F). Cover the solder surface with 5744 by sprinkling the powder on the pot in a thin covering layer, no greater than 6.4mm (0.25in) thick. Slowly mix the salt with the surface of the solder with a metallic solder ladle or a metal spatula. Allow the salt 10 seconds after mixing to convert the dross back to solder. Move any dross on the pot into the salt covered surface to convert the dross to metal. When done, remove the dross recovery salt and other dirt residues with a metallic solder ladle or a metal spatula. All of the 5744 should be removed from the solder surface. 5744 is intended to be used as received.



Storage, Handling and Shelf Life

5744 should be stored in sealed containers. Shelf life is 3 years from date of manufacture when handled properly and held at -10-45°C (14-113°F).



Health and Safety

This product, during handling or use, may be hazardous to your health or the environment. Read the Safety Data Sheet and warning label before using this product. Safety Data Sheets are available at <https://www.kester.com/downloads/sds>.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9