

CentralTM Semiconductor Corp.

145 Adams Avenue, Hauppauge, NY 11788 USA

Tel: (631) 435-1110 • Fax: (631) 435-1824

Manufacturers of World Class Discrete Semiconductors

2N5879 2N5880 PNP

2N5881 2N5882 NPN

COMPLIMENTARY SILICON
POWER TRANSISTORS

JEDEC TO-3 CASE

DESCRIPTION

The CENTRAL SEMICONDUCTOR 2N5879, 2N5881 series types are Complimentary Silicon Power Transistors manufactured by the epitaxial base process, mounted in a hermetically sealed metal case designed for general purpose switching and amplifier applications.

MAXIMUM RATINGS ($T_C=25^\circ\text{C}$)

	SYMBOL	2N5879 2N5881	2N5880 2N5882	UNIT
Collector-Base Voltage	V_{CB0}	60	80	V
Collector-Emitter Voltage	V_{CE0}	60	80	V
Emitter Base Voltage	V_{EB0}		5.0	V
Collector Current	I_C		15	A
Collector Current (PEAK)	I_{CM}		30	A
Base Current	I_B		5.0	A
Power Dissipation	P_D		160	W
Operating and Storage Junction and Temperature	T_J, T_{stg}	-65 TO +200		$^\circ\text{C}$
Thermal Resistance	θ_{JC}		1.1	$^\circ\text{C/W}$

ELECTRICAL CHARACTERISTICS ($T_C=25^\circ\text{C}$ unless otherwise noted)

SYMBOL	TEST CONDITIONS	2N5879 2N5881		2N5880 2N5882		UNIT
		MIN	MAX	MIN	MAX	
V_{CB0}	$V_{CB}=\text{RATED}$ V_{CB0}		0.5		0.5	mA
I_{CEV}	$V_{CE}=\text{RATED}$ $V_{CE0}, V_{BE}=1.5\text{V}$		0.5		0.5	mA
I_{CEV}	$V_{CE}=\text{RATED}$ $V_{CE0}, T_C=150^\circ\text{C}$		5.0		5.0	mA
I_{CE0}	$V_{CE}=\frac{1}{2}\text{RATED}$ V_{CE0}		1.0		1.0	mA
I_{EB0}	$V_{EB}=5.0\text{V}$		1.0		1.0	mA
BV_{CE0}	$I_C=200\text{mA}$	60		80		V
$V_{CE}(\text{SAT})$	$I_C=7.0\text{A}, I_B=0.7\text{A}$		1.0		1.0	V
$V_{CE}(\text{SAT})$	$I_C=15\text{A}, I_B=3.75\text{A}$		4.0		4.0	V
$V_{BE}(\text{SAT})$	$I_C=15\text{A}, I_B=3.75\text{A}$		2.5		2.5	V
$V_{BE}(\text{ON})$	$V_{CE}=4.0\text{V}, I_C=6.0\text{A}$		1.5		1.5	V
h_{FE}	$V_{CE}=4.0\text{V}, I_C=2.0\text{A}$	35		35		
h_{FE}	$V_{CE}=4.0\text{V}, I_C=6.0\text{A}$	20	100	20	100	
h_{FE}	$V_{CE}=4.0\text{V}, I_C=15\text{A}$	4.0		4.0		
h_{fe}	$V_{CE}=4.0\text{V}, I_C=2.0\text{A}, f=1.0\text{kHz}$	20		20		
f_T	$V_{CE}=10\text{V}, I_C=1.0\text{A}, f=1.0\text{MHz}$	4.0		4.0		MHz
C_{ob}	$V_{CB}=10\text{V}, I_E=0, f=100\text{kHz}$ (PNP TYPES)		600		600	pF
C_{ob}	$V_{CB}=10\text{V}, I_E=0, f=100\text{kHz}$ (NPN TYPES)		400		400	pF
t_r	$V_{CC}=30\text{V}, I_C=6.0\text{A}, I_{B1}=I_{B2}=0.6\text{A}$		0.7		0.7	μs
t_s	$V_{CC}=30\text{V}, I_C=6.0\text{A}, I_{B1}=I_{B2}=0.6\text{A}$		1.0		1.0	μs
t_f	$V_{CC}=30\text{V}, I_C=6.0\text{A}, I_{B1}=I_{B2}=0.6\text{A}$		0.8		0.8	μs

OUTSTANDING SUPPORT AND SUPERIOR SERVICES



PRODUCT SUPPORT

Central's operations team provides the highest level of support to insure product is delivered on-time.

- Supply management (Customer portals)
- Inventory bonding
- Consolidated shipping options
- Custom bar coding for shipments
- Custom product packing

DESIGNER SUPPORT/SERVICES

Central's applications engineering team is ready to discuss your design challenges. Just ask.

- Free quick ship samples (2nd day air)
- Online technical data and parametric search
- SPICE models
- Custom electrical curves
- Environmental regulation compliance
- Customer specific screening
- Up-screening capabilities
- Special wafer diffusions
- PbSn plating options
- Package details
- Application notes
- Application and design sample kits
- Custom product and package development

REQUESTING PRODUCT PLATING

1. If requesting Tin/Lead plated devices, add the suffix " TIN/LEAD" to the part number when ordering (example: 2N2222A TIN/LEAD).
2. If requesting Lead (Pb) Free plated devices, add the suffix " PBFREE" to the part number when ordering (example: 2N2222A PBFREE).

CONTACT US

Corporate Headquarters & Customer Support Team

Central Semiconductor Corp.
145 Adams Avenue
Hauppauge, NY 11788 USA
Main Tel: (631) 435-1110
Main Fax: (631) 435-1824
Support Team Fax: (631) 435-3388
www.centrasemi.com

Worldwide Field Representatives:
www.centrasemi.com/wwreps

Worldwide Distributors:
www.centrasemi.com/wwdistributors

For the latest version of Central Semiconductor's **LIMITATIONS AND DAMAGES DISCLAIMER**, which is part of Central's Standard Terms and Conditions of sale, visit: www.centrasemi.com/terms

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9