

Dieses Dokument ist urheberrechtlich geschützt • This document is protected by copyright • Rosenberger Hochfrequenztechnik GmbH & Co. KG
RF_35/05.10/6.1

Technical Data Sheet		Rosenberger
RPC-N 50 Ω	GAUGE KIT	06GK0KS-010



Picture may differ from original product.

Contents

Device	Part number	Quantity	Calibration Option ^a
Gauge plug (including gauge block)	06W00S-000	1	FC
Gauge jack (including gauge block)	06W00K-000	1	FC

a. See "Declaration of calibration options" for explanation.

Mechanical specifications

	06W00S-000	06W00K-000
Gauge block	5.28 mm	5.28 mm
Gauge range	5.28 mm ± 0.5 mm	5.28 mm ± 0.5 mm
Scale gradation	1 µm	1 µm
Limit of measurement error ¹	≤ 10 µm ²	≤ 10 µm ³
Typical measurement error ¹	≤ 6 µm ²	≤ 6 µm ³
Measuring force	1.5 N	1.5 N

¹ When zeroed with gauge block

² 5.24 mm to 5.40 mm

³ 5.16 mm to 5.32 mm

Documentation

This kit is delivered with

- **Calibration Certificate**
Details see "Declaration of calibration options"
- **Kit Info Card**
Handling precautions and mechanical information.
- **Operating Manual**

Declaration of calibration options

Factory Calibration

Standard delivery for this gauge includes a Factory Calibration. The Calibration Certificate issued reports individual mechanical calibration results, traceable to national / international standards.

Accredited Calibration

Not available.

For further, more detailed information see application note AN001 on the Rosenberger homepage.

Calibration interval

Recommendation	12 months
----------------	-----------

For further, more detailed information please visit our homepage www.rosenberger.com.

While the information has been carefully compiled to the best of our knowledge, nothing is intended as representation or warranty on our part and no statement herein shall be construed as recommendation to infringe existing patents. In the effort to improve our products, we reserve the right to make changes judged to be necessary.

Draft	Date	Approved	Date	Rev.	Engineering change number	Name	Date
Martin Moder	23/11/15	Roland Neuhauser	06.11.18	c00	18-0004	M.Ruf	06.11.18
Rosenberger Hochfrequenztechnik GmbH & Co. KG P.O.Box 1260 D-84526 Tittmoning Germany www.rosenberger.de				Tel. : +49 8684 18-0 Email : info@rosenberger.de			Page 2 / 2

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9