

2000W 230V AVR Line Conditioner, Power Conditioner, AC Surge Protector, 6 Outlets, Uniplug adapter

MODEL NUMBER: LR2000



Description

Tripp Lite's LR2000 Automatic Voltage Regulation/AVR power conditioner prevents equipment damage, performance problems and system degradation due to voltage fluctuations, line noise and transient surges. Ensures 230V +/-10% output voltage for computer equipment, home theater systems and other sensitive electronic devices during brownouts to 175 and overvoltages to 253V. Reliable transformer-based voltage regulation offers two available levels of voltage boost to correct severe undervoltages, along with a single level of voltage reduction for overvoltages. Network-grade AC surge and EMI/RFI noise suppression removes power contaminants known to cause system interference, lockups and power-related audio and video artifacts. Extends the useful life of connected equipment by enhancing power supply efficiency and preventing overtemperature conditions. Front panel LEDs offer metered verification of input voltage level in 3 stages. Detachable IEC-320 C14 connector accepts a variety of worldwide replacement cordsets. Includes 6 outlets (2 NEMA 5-15R, 2 NEMA 6-15R and 2 IEC-320 C13), plus one UNIPLUG adapter capable of accommodating dozens of international plug types.

Features

- Maintains regulated 208/220/240V nominal output (selectable).
- Three levels of voltage stabilization offer targeted response to overvoltages, undervoltages and severe brownouts
- Input voltages over 255V (@240V)/234V (@220V)/221V (@208V) are reduced by 9.8%
- Input voltages between 204-223V (@240V)/ 189-204V (@220V)/ 179-193V (@208V) are boosted by 9%
- Input voltages at or below 205V (@240V)/ 188V (@220V)/ 178 (208V)are boosted by 18.2%
- 2000 watts output power rating supports up to 8.7 amps
- Network grade AC surge suppression
- EMI/RFI noise filtering
- 5 diagnostic LEDs indicate boost, trim and normal AVR operation
- 6 protected outlets (2 NEMA 5-15R/2 NEMA 6-15R/2 IEC-320 C13)
- IEC-320 C14 inlet connection supports user supplied country specific equipment cord set

Highlights

- Automatic Voltage Regulation - AVR System maintains 230V +/-10%
- Corrects brownouts to 175V and overvoltages to 281V
- Reliable single-cut, dual-boost transformer based voltage correction
- 6 Outlets (2 5-15R, 2 6-15R & 2 C13), 1 UNIPLUG adapter
- 2000 watts

Applications

- Ideal for use with computer accessories, laser printers, home theater and professional A/V systems, POS equipment and other sensitive electronic devices

Package Includes

- LR2000 Line Conditioner
- 2m C13 to NEMA 6-15P cord set
- One UNIPLUG international plug adapter
- Instruction manual and warranty information



Specifications

OUTPUT	
Nominal Output Voltage(s) Supported	230V
Output Receptacles	(2) 5-15R; (2) C13; (2) 6-15R
Output (Watts)	2000
Outlet Details	Includes 1 uniplug adapter that converts one of the built-in outlets to accept a variety of country specific plug types
INPUT	
Maximum Input Amps / Watts	10A
Input Cord Length (ft.)	6.5
Input Cord Length (m)	2
USER INTERFACE, ALERTS & CONTROLS	
Front Panel LEDs	5 LEDs show incoming voltage status (Very Low / Low / Normal / High / Very High)
SURGE / NOISE SUPPRESSION	
UPS AC Suppression Joule Rating	1200
EMI / RFI AC Noise Suppression	75 dB
PHYSICAL	
Shipping Weight (lbs.)	8.8
Shipping Weight (kg)	4
Unit Dimensions (hwd / in.)	7 x 6 x 7
Unit Dimensions (hwd / cm)	17.8 x 15.2 x 17.8
Material of Construction	Polycarbonate
Form Factors Supported	Small tower placement supported
WARRANTY	
Product Warranty Period (International)	2-year limited warranty
Product Warranty Period (Mexico)	2-year limited warranty
Product Warranty Period (Puerto Rico)	2-year limited warranty



Tripp Lite
1111 W. 35th Street
Chicago, IL 60609 USA
Telephone: 773.869.1234
www.tripplite.com

Specifications are subject to change without notice. Photos may differ slightly from final products.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9