

DBR Direct Bury Splice Kit

Application:

Use part DBR, which includes a Scotchlok® R Electrical Spring Connector, to electrically connect two or more pre-stripped copper wire ends in a pigtail application and moisture seal the connection for direct burial.

Wire:

Common AWG wire combinations
(Copper wire only, sol or str)

2 – 3 # 10	1 # 10 to 1 # 12
2 – 4 # 12	1 # 10 to 1 or 2 # 14
3 – 4 # 14	1 # 12 to 1 to 3 # 14
4 – 6 # 16	1 # 12 to 2 or 3 # 16
	1 # 14 to 2 or 3 # 16

Consult technical service for complete list of wire combinations.

Construction:

Connector – steel spring , shell , flame retardant pvc insulator
Tube – polypropylene
Gel – thixotropic calcium organic complex

Application Data:

Application Temperature: 32°F to 120°F
(0°C to 40°C)

Operating Temperature: 221°F to –40°F
(105°C to –40°C)

Voltage Rating: 30 Volts


Not for use in direct ultraviolet exposure

Weight of one kit: (2 splices) .0990 lbs
(44,94 gm)

Storage: Do not store above 120°F (49°C)

Engineering Specification:

The device, 3M Brand DBR Direct Bury Splice Kit, shall splice and effectively moisture seal two or more conductors. The electrical connector shall be a Scotchlok® R. The device shall be installed per manufacturer's instructions and all applicable codes.



IMPORTANT NOTICE TO PURCHASER:

All statements, technical information and recommendations related to the Seller's products are based on information believed to be reliable, but the accuracy or completeness thereof is not guaranteed. Before utilizing the product, the user should determine the suitability of the product for its intended use. The user assumes all risks and liability whatsoever in connection with such use.

All statements or recommendations of the seller which are not contained in the Seller's current publications shall have no force or effect unless contained in an agreement signed by an authorized officer of the Seller. The statements contained herein are made in lieu of all warranties express or implied, including but not limited to the implied warranties of merchantability and fitness for a particular purpose which warranties are hereby expressly disclaimed.

SELLER SHALL NOT BE LIABLE TO THE USER OR ANY OTHER PERSON UNDER ANY LEGAL THEORY, INCLUDING BUT NOT LIMITED TO NEGLIGENCE OR STRICT LIABILITY, FOR ANY INJURY OR FOR ANY DIRECT OR CONSEQUENTIAL DAMAGES SUSTAINED OR INCURRED BY REASON OF THE USE OF ANY OF THE SELLER'S PRODUCTS.

Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9