

HEDL-550x/554x, HEDL-560x/564x, HEDL-9000/9100, HEDL-9040/9140/ 92xx Encoder Line Drivers



Data Sheet



Description

Line Drivers are available for the HEDS-55xx/56xx series and the HEDS-9000/9100/9200/9040/9140 series encoders. The line driver offers enhanced performance when the encoder is used in noisy environments, or when it is required to drive long distances.

The encoder line driver utilizes an industry standard line driver IC, AM26C31Q, which provides complementary outputs for each encoder channel. Thus, the output of the line driver encoder is A, \bar{A} , B, \bar{B} and I/ \bar{I} for three channel versions. Suggested line receivers are 26LS32 and 26LS33.

For additional information, please refer to:

HEDS-5500/5540/5600/5640 data sheet,

HEDS-90x0/91x0/92x0 data sheets,

HEDS-9000 series extended resolution data sheet, and AM26C31Q data sheet.

Features

- Available on Both Encoder Modules (HEDS-9000 Series) and Encoder Kit Housing (HEDS-5500 Series)
- Complementary Outputs
- Industry Standard Line Driver IC
- Single 5 V Supply
- Onboard Bypass Capacitor

Note: Avago Technologies encoders are not recommended for use in safety critical applications. Eg. ABS braking systems, power steering, life support systems and critical care medical equipment. Please contact sales representative if more clarification is needed.

Device Characteristics

| Parameter | Characteristic | Notes |
|-----------------------------|---|--|
| Termination | 10 conductor ribbon cable with 10 position IDC connector | See pinout |
| Electrical Outputs | Complementary outputs: A, \bar{A} , B, \bar{B} , I, \bar{I} | I and \bar{I} available only on three channel encoders |
| Line Driver Components | AM26C31Q line driver IC, decoupling capacitor on PC board. | |
| Operating Temperature Range | -40°C to 100° C | 100° C Series |
| Storage Temperature | -40°C to 100° C | 100° C Series |

ESD WARNING: NORMAL HANDLING PRECAUTIONS SHOULD BE TAKEN TO AVOID STATIC DISCHARGE.

Line Driver Package Dimensions

For Detailed Dimensions on encoder packages, please refer to the respective data sheets.



HEDL-550X/554X/560X/564X

NOTE: DIMENSIONS IN MILLIMETERS (INCHES)



HEDL-9000/9100/9200/9040/9140

Waveforms



Block Diagram



Pinouts

10-PIN CONNECTOR

| NO. | COLOR | PARAMETER |
|-----|--------|-------------------------|
| 1 | BROWN | NC |
| 2 | RED | V _{CC} (+ 5 V) |
| 3 | ORANGE | GND |
| 4 | YELLOW | NC |
| 5 | GREEN | Ā |
| 6 | BLUE | A |
| 7 | VIOLET | B̄ |
| 8 | GREY | B |
| 9 | WHITE | Ī (INDEX) |
| 10 | BLACK | I (INDEX) |



10 POSITION IDC CONNECTOR
CENTER POLARIZED.

Note: Ī only available on three channel encoders.

Line Driver Base Parts Available:

| 100°C Line Driver Base Part | Channels | Refer to the following encoder data sheet for additional information and option codes (XXX = resolution and/or shaft size) |
|--------------------------------|----------|--|
| HEDL-5500#XXX | A, B | HEDS-5500#XXX |
| HEDL-5505#XXX | A, B | HEDS-5505#XXX |
| HEDL-5540#XXX | A, B, I | HEDS-5540#XXX |
| HEDL-5600#XXX | A, B | HEDS-5600#XXX |
| HEDL-5605#XXX | A, B | HEDS-5605#XXX |
| HEDL-5640#XXX | A, B, I | HEDS-5640#XXX |
| HEDL-5645#XXX | A, B, I | HEDS-5645#XXX |
| HEDL-9000#XXX | A, B | HEDS-9000#XXX |
| HEDL-9040#XXX | A, B, I | HEDS-9040#XXX |
| HEDL-9100#XXX | A, B | HEDS-9100#XXX |
| HEDL-9140#XXX | A, B, I | HEDS-9140#XXX |

Ordering Information:

For option code selection, refer to the data sheet for the corresponding “HEDS” part number (see right column).

| | | 01 | 02 | 04 | 05 | 06 | 11 | 12 | 13 | 14 |
|------------|---|----|----|----|----|----|----|----|----|----|
| HEDL-5500# | A | | * | | | * | | | | |
| | E | | | | | * | | | | |
| | G | | | | * | | | * | | |
| | H | | | | | * | | | | |
| | I | | | * | | | | | | |
| HEDL-5505# | A | | | | | * | | | | |
| | I | | | | | | | | * | |
| HEDL-5540# | A | * | * | | * | * | * | * | * | * |
| | C | | * | | * | | | * | | |
| | E | | | | | * | * | | | |
| | G | | | | | | * | | | |
| | I | * | | | | * | * | | * | |
| HEDL-5600# | A | | | | | * | | | | |
| | H | | | | | * | | | | |
| HEDL-5605# | A | | | | | * | | | | |
| | C | | | | | | | | | * |
| HEDL-5640# | A | | | | | * | | * | * | |
| HEDL-5645# | A | | | | | * | | | * | |
| | G | | | | | * | | | | |

| | |
|------------|---------|
| HEDL-9000# | U00 |
| HEDL-9040# | B00 |
| HEDL-9100# | A00 |
| HEDL-9140# | A00 I00 |

For product information and a complete list of distributors, please go to our web site: www.avagotech.com

Avago, Avago Technologies, and the A logo are trademarks of Avago Technologies, Limited in the United States and other countries.
 Data subject to change. Copyright © 2006 Avago Technologies Pte. All rights reserved. Obsoletes 5989-4105EN
 AV02-0993EN - January 30, 2008



Данный компонент на территории Российской Федерации

Вы можете приобрести в компании MosChip.

Для оперативного оформления запроса Вам необходимо перейти по данной ссылке:

<http://moschip.ru/get-element>

Вы можете разместить у нас заказ для любого Вашего проекта, будь то серийное производство или разработка единичного прибора.

В нашем ассортименте представлены ведущие мировые производители активных и пассивных электронных компонентов.

Нашей специализацией является поставка электронной компонентной базы двойного назначения, продукции таких производителей как XILINX, Intel (ex.ALTERA), Vicor, Microchip, Texas Instruments, Analog Devices, Mini-Circuits, Amphenol, Glenair.

Сотрудничество с глобальными дистрибьюторами электронных компонентов, предоставляет возможность заказывать и получать с международных складов практически любой перечень компонентов в оптимальные для Вас сроки.

На всех этапах разработки и производства наши партнеры могут получить квалифицированную поддержку опытных инженеров.

Система менеджмента качества компании отвечает требованиям в соответствии с ГОСТ Р ИСО 9001, ГОСТ РВ 0015-002 и ЭС РД 009

Офис по работе с юридическими лицами:

105318, г.Москва, ул.Щербаковская д.3, офис 1107, 1118, ДЦ «Щербаковский»

Телефон: +7 495 668-12-70 (многоканальный)

Факс: +7 495 668-12-70 (доб.304)

E-mail: info@moschip.ru

Skype отдела продаж:

moschip.ru

moschip.ru_4

moschip.ru_6

moschip.ru_9